


DIGITAL LUX (LIGHT) METER		Model: <i>indi</i> 6171
Specification:		
Display	3½ Digit, 13mm LCD	 <p>Detachable Sensor</p>
Range	0-2000, 0-20000 & 0-50000 Lux (3 Ranges)	
Resolution	0-2000(1 Lux), 0-20000(10 Lux) & 0-50000(100 Lux), (3 Ranges)	
Range Selection	By Switch	
Accuracy	±(5% + 2 Digit)	
Sensor	Photo diode with color correction Filter & COS Correction	
Sampling Time	0.4 times / Seconds	
Zero Adjustment	Internal	
Over Range	"1" indicated	
Operating Humidity	Less than 80% RH	
Battery	9V Battery	
Data Hold	Provided	
Cabinet Size	131 x 70 x 25 mm	
Carrying Case	Provided	

DIGITAL LUX (LIGHT) METER		Model: <i>indi</i> 6172
Specification:		
Display	3½ Digit, 13mm LCD	 <p>Detachable Sensor</p>
Range	0-2000, 0-20000 & 0-100,000 Lux (3 Ranges)	
Resolution	0-2000(1 Lux), 0-20000(10 Lux) & 0-100000(100 Lux), (3 Ranges)	
Range Selection	By Switch	
Accuracy	<10,000 Lux: ±(4% reading ±0.5 F S) >10,000 Lux: ±(5% + 10 Digit)	
Sensor	Silicon Photo diode with color correction Filter & COS Correction	
Sampling Time	0.2 times / Seconds	
Zero Adjustment	Internal	
Over Range	"1" or "OVER" indicated	
Operating Humidity	Less than 80% RH	
Battery	9V Battery	
Data Hold	Provided	
Cabinet Size	106 x 57 x 26 mm	
Carrying Case	Provided	

<p>Source 1 INSTRUMENTS</p> <p>Plot No. L/715/10, 40 Shed Area, GIDC, Vapi – 396195. Gujarat. India.</p> <p>Tel: (0260) 325 1066 Fax: (0260) 2401654 Mob: 93770 29027 / 98244 64050</p> <p>Email: sales@source1in.com source1in@indiatimes.com URL: www.source1in.com</p> <p>Branch Offices: Rajkot Baroda Surat Ahmedabad Chandigarh Nashik Pune Coimbatore</p>	<p>3 YEAR*</p> <p>REPLACEMENT</p> <p>WARRANTY</p>
---	--